IN THE CLAIMS:

Please **CANCEL** claim 24 without prejudice or disclaimer.

Please **AMEND** claims 1, 12, 23, 25-26, and 35-36 and as shown below.

1.   (Currently Amended) A method for detecting an assumed octet slip in an inband signalling block in pulse code modulation, the method comprising:

~~choosing a searching direction;~~

searching a first error <u>at a position</u> bit k1 starting from a<u>n</u> ~~chosen~~ end of a searching block<u>, the searching block comprising a set of bits</u>;

counting a number of bit errors starting from ~~said~~ <u>a corresponding position</u> k1 ~~bit~~ in a slipped block<u>, the slipped block being another set of bits where each bit is shifted relatively to a corresponding bit of the searching block</u>; and

detecting octet slip by analyzing the error bits.

2.   (Original) The method according to claim 1, wherein when the chosen direction is from a first bit to a last bit, the searching block is a signalling block and the slipped block is adjacent block.

3.   (Original) The method according to claim 1, wherein when the chosen direction is from a last bit to a first bit, the searching block is an adjacent block and the slipped block is a signalling block.

Application No.: 10/662,122

4. (Original) The method according to claim 3, further comprising verifying a correctness of the signalling block before searching.

5. (Original) The method according to claim 2, wherein searching and counting bit errors is performed by comparing the signalling block and the adjacent block to a sample block.

6. (Original) The method according to claim 2, wherein the octet slip is detected starting from or after the bit $k1$ if the number of the bit errors in the slipped block is more than one.

7. (Original) The method according to claim 2, wherein the octet slip is detected before the bit $k1$ if the number of error bits starting from the bit $k1$ is zero or one.

8. (Original) The method according to claim 6, further comprising searching a second error bit $k2$ of the searching block starting from a bit after the first error bit $k1$.

9. (Original) The method according to the claim 8, further comprising detecting if the bits of the slipped block starting from the second error bit $k2$ are correct.

Application No.: 10/662,122

10.   (Original) The method according to the claim 9, further comprising detecting that the octet slip between the error bits k1 and k2 and the number of bit errors is one if the bits in the slipped block starting from the second error bit k2 are correct.

11.   (Original) The method according to the claim 9, further comprising determining that the octet slip cannot be detected if the number of bit errors is more than one.

12.   (Currently Amended) A device for detecting an assumed octet slip in an inband signalling block in pulse code modulation, which device is connected to in path equipment, the system comprising a slip detector, said slip detector the device comprising:

means for choosing a searching direction;

a searcher arranged to search a first error bit at a position k1 starting from an chosen end of a searching block, the searching block comprising a set of bits;

a counter arranged to count a number of bit errors starting from said a corresponding po9sition k1 bit in a slipped block, the slipped block being another set of bits where each bit is shifted relatively to a corresponding bit of the searching block; and

a detector arranged to detect the octet slip by analyzing error bits.

13.   (Original) The device according to claim 12, wherein if the chosen direction is from a first bit to a last bit the device is arranged to set the searching block to correspond to a signalling block and the slipped block to correspond to an adjacent block.

14.   (Original) The device according to claim 12, wherein if the chosen direction is from a last bit to a first bit the device is arranged to set the searching block to correspond to an adjacent block and the slipped block to correspond to a signalling block.

15.   (Original) The device according to claim 14, wherein the device is arranged to verify a correctness of the signalling block before searching.

16.   (Original) The device according to claim 13, wherein the searcher is arranged to search bit error by comparing the signalling block and the adjacent block to a sample block.

17.   (Original) The device according to claim 13, wherein the detector is arranged to detect the octet slip starting from or after the bit k1, if the number of bit errors in the slipped block is more than one.

Application No.: 10/662,122

18.   (Original) The device according to claim 13, wherein the detector is arranged to detect the octet slip before the bit k1 if the number of bit errors starting from the bit k1 is zero or one.

19.   (Original) The device according to claim 17, wherein searcher is arranged to search a second error bit k2 of the searching block starting from a bit after the first error bit k1.

20.   (Original) The device according to the claim 19, wherein the detector is arranged to detect if bits of the slipped block starting from the second error bit k2 are correct.

21.   (Original) The device according to the claim 20, wherein the detector is arranged to detect that the octet slip between the error bits k1 and k2 and the error count is one if the bits starting from the error bit k2 are correct.

22.   (Original) The device according to the claim 21, wherein the detector is arranged to determine that the octet slip cannot be detected if the number is more than one.

Application No.: 10/662,122

23.	(Currently Amended) A system for detecting an assumed octet slip in an inband signalling block in pulse code modulation, which system comprises:

a sender terminal transmit a signal;

a receiver terminal;

an in path equipment; and

a slip detector that is arranged to detect assumed octet slip, the slip detector comprising,

a searcher arranged to search a first error bit at a position k1 starting from an end of a searching block, the searching block comprising a set of bits,

a counter arranged to count a number of bit errors starting from a corresponding position k1 in a slipped block, the slipped block being another set of bits where each bit is shifted relatively to a corresponding bit of the searching block, and

a detector arranged to detect the octet slip by analyzing error bits.

24.	(Cancelled)

25.	(Currently Amended) The system according to claim 2423, wherein if the chosen direction is from a first bit to the last bit the device is arranged to set the searching block to correspond to a signalling block and the slipped block to correspond to an adjacent block.

Application No.: 10/662,122

26.   (Currently Amended) The system according to claim ~~24~~23, wherein if the chosen direction is from a last bit to a first bit the device is arranged to set the searching block to correspond to an adjacent block and the slipped block to correspond to a signalling block.

27.   (Original) The system according to claim 26, wherein the device is arranged to verify a correctness of the signalling block before searching.

28.   (Original) The system according to claim 25, wherein the searcher is arranged to search bit error by comparing the signalling block and the adjacent block to a sample block.

29.   (Original) The system according to claim 25, wherein the detector is arranged to detect the octet slip starting from or after the bit k1, if the number of the bit errors in the slipped block is more than one.

30.   (Original) The system according to claim 25, wherein the detector is arranged to detect the octet slip before the bit k1 if the number of bit errors starting from the bit k1 is zero or one.

Application No.: 10/662,122

31.   (Original) The system according to claim 29, wherein the searcher is arranged to search a second error bit k2 of the searching block starting from a bit after the first error bit k1.

32.   (Original) The system according to claim 31, wherein the detector is arranged to detect if the bits of the slipped block starting from the second error bit k2 are correct.

33.   (Original) The system according to claim 32, wherein the detector is arranged to detect that the octet slip between the error bits k1 and k2 and the number of bit errors is one if the bits starting from the error bit k2 are correct.

34.   (Original) The system according to claim 33, wherein the detector is arranged to determine that the octet slip cannot be detected if the number is more than one.

35.   (Currently Amended) The system according to claim 24 23 wherein the slip detector is arranged into the path equipment.

36.   (Currently Amended) The system according to the claim 24 23, wherein the slip detector is arranged into the receiver terminal.

Application No.: 10/662,122